











Smoothie Data Sheet






Specifications

Plate Material	304 Grade stainless steel
Finish Applied on Plate	Electrophoretic Prime Paint (Primed for Painting)
Single Plate Dimensions	90.8mm x 90.8mm
Twin Plate Dimensions	153.2mm x 90.8mm
Screw Type	N/A
Plate Prefix	FS
Standard Insert Trim Colour	White or Black

Standard Brochure Items

	Product	Description	Plate Size	Wall box
	*-Insert Colour B-Black W-White	ROCKER GRID SWITCHES (Metal Switch Caps)		
	11.1*	1 Gang 20AX 2 Way rocker switch	90.8x90.8mm	35mm Single
	11.1*/2	1 Gang 20AX double pole switch	90.8x90.8mm	35mm Single
	11.1*/3	1 Gang 20AX intermediate switch	90.8x90.8mm	35mm Single
	11.1*/4	1 Gang 20AX 2 Way and off switch	90.8x90.8mm	35mm Single
	11.1*/5	1 Gang 20 Amp retractive switch	90.8x90.8mm	35mm Single
	11.1*/7	1 Gang 20 Amp 2 Way and off retractive switch	90.8x90.8mm	35mm Single
	11.2*	2 Gang 20AX 2 Way switch	90.8x90.8mm	35mm Single
	11.3*	3 Gang 20AX 2 Way switch	153.2x90.8mm	35mm Twin

	11.4*	4 Gang 20AX 2 Way switch	153.2x90.8mm	35mm Twin
		ROCKER GRID SWITCHES (Plastic Switch Caps)		
	10.1*	1 Gang 20AX 2 Way switch	90.8x90.8mm	35mm Single
	10.1*/2	1 Gang 20AX double pole switch	90.8x90.8mm	35mm Single
	10.1*/3	1 Gang 20AX intermediate switch	90.8x90.8mm	35mm Single
	10.1*/4	1 Gang 20AX 2 Way and off switch	90.8x90.8mm	35mm Single
	10.1*/5	1 Gang 20 Amp retractive switch	90.8x90.8mm	35mm Single
	10.1*/7	1 Gang 20 Amp 2 Way and off retractive switch	90.8x90.8mm	35mm Single
	10.2*	2 Gang 20AX 2 Way switch	90.8x90.8mm	35mm Single
	10.3*	3 Gang 20AX 2 Way switch	153.2x90.8mm	35mm Twin

	10.4*	4 Gang 20AX 2 Way switch	153.2x90.8mm	35mm Twin
		UNSWITCHED SOCKET OUTLETS		
	19.1*	1 Gang 2 Amp	90.8x90.8mm	35mm Single
	20.1*	1 Gang 5 Amp	90.8x90.8mm	35mm Single
	17.1*/US	1 Gang 13 Amp	90.8x90.8mm	35mm Single
	17.2*/US	2 Gang 13 Amp	153.2x90.8mm	35mm Twin

Bespoke Accessories

Focus SB can produce and manufacture some bespoke accessories including combination plates to meet your exact requirements in this range. Please contact one of our product consultants for further details.

Fitting of Products

All electrical products must be fitted by a fully qualified electrician, failure to adhere to this voids any warranty on the products.

Installation Instructions

Each grid, with the electrical insert assembled, is numbered and must be used with the correspondingly numbered wall box. They would normally be supplied assembled together.

The front plates will be provided in a primed condition for customer finishing as required.

The grid can be screwed back in the box and covered with **the supplied discard-able perspex sheet to offer** protection from the plastering, or, as it will have to be wired in, be removed completely as long as it is returned to its' correct box. The four screws must be removed in a uniform manner so as to not distort the grid plate.

It would normally be expected that the perforated plastering ring would be laid on top of the rendering and the wall box carefully screwed back to the wall without any undue distortion of the frame.

The final top coat of plaster would then be applied making sure it is forcibly applied close to the aperture so there is a good bond to the ring.

The plaster can be either cut back, accurately, so it is level with the top edge of the stainless steel ring, or, over plastered and sanded back until the ring just appears.

The insert can now be wired up and the complete grid assembly re-fitted to the box. Please make sure the dished washers are fitted correctly.

All four screws of the grid must be screwed in, in a uniform manner to avoid any distortion of the grid.

Careful setting of the depth **of the grid** will allow the front plate to sit perfectly flat and recessed into the wall.

Standards Conformance

All switches are designed and tested to BS EN 60669-1 and are suitable for UK metal flush boxes to BS4662. Boxes, plates and grids must be earthed and if fitted outside the UK permission/approval must be obtained by the local or national electricity supplier and/or approvals authority.

13 amp sockets conform to BS1363
5 amp & 2 amp sockets conform to BS546

All products are UKCA marked and comply with UK safety, EMC and environmental regulation where applicable.

All products are CE marked and comply with UK safety, EMC and environmental directives where applicable.

All products supplied by Focus SB in this range in compliance with The EU REACH Directive No 1907/2006 with respect to Substances/Chemical classified as SVHC

Warranty

Interiors: 12-month manufacturer warranty against product fault

Plates: 12-month manufacturer warranty against product fault

Contact Details

Focus SB Ltd
Napier Road
St Leonards on Sea
East Sussex
TN38 9NY
England

Tel: +44 (0)1424 858060

Fax: +44 (0)1424 853862

Email: sales@focus-sb.co.uk

Web: www.focus-sb.co.uk



FS691298